



THE EASTERN SPECIALTY COMPANY

10 AMP CURRENT TRANSFORMER BURDEN TEST SET

CAT. 1043

FUNCTIONALITY

The **Catalog 1043 Current Transformer Burden Test Set** is a simple and inexpensive means whereby a current transformer installation may be quickly checked for many sources of trouble. The tests are made without interrupting the customer's service and while the load is on.

The instrument is essentially a multi-range ammeter with a built-in ohmic burden which is normally shunted, but which can be put in series with the meter by pressing a push button.

Extensive precautions have been taken in the design of the CT Burden Test Set. A continuous and closed path in the watt-hour meter current circuit exists at all times, and the secondary of the current transformer will not open by accident.

FEATURES

- Current ranges selected such that a half-scale reading on any range will be a full-scale deflection on the next lowest range. Consequently, a current range can be selected which will give at least half-scale deflection.
- Large, easy to read panel meter.
- Four current ranges
- Six ohmic burden values
- Non-conducting molded case

SPECIFICATIONS

- **Current Ranges:** 1.25, 2.5, 5, 10 amperes
- **Burden Values:** 0.1, 0.2, 0.5, 1.0, 2.0, 4.0 ohms At the nominal current of 5 amperes, these ohmic values correspond to 2.5, 5, 12.5, 25, 50 and 100 volt ampere burden, respectively.
- **Rotary Switches:** The rotary switches are of the shorting or "make before break" type to prevent accidental opening of the C. T. secondary.
- **Readability:** The meter is a 2.5" panel instrument with a scale of 2.2" and a transparent unbreakable plastic cover for easy viewing.
- **Duty Cycle:** The instrument is rated for continuous duty up to the largest current value except for the burden resistors which are rated for intermittent duty.
- **Case:** The instrument is housed in a non-conducting black molded plastic case with white panel markings.
- **Dimensions:** 5.25" x 6.875" x 3.125" (W x H x D)
- **Weight:** 2.75 lbs

