



TESCO METERING

Reliable Results. Every Meter. Every Time.



925 Canal Street, Bristol, PA 19007

• 215.228.0500

• tescometering.com

Field Testing

Catalog No.

P02-0802

Fiber Optic Coupled Ammeter

PRODUCT INTRODUCTION

The TESCO Fiber Optic Coupled Ammeter was developed using current sensor technology. It is a two-piece, True RMS ammeter with a fiber optic link between the high voltage sensor and the readout at ground potential. The sensor is mounted on a hotstick and slipped over a high voltage line.





TESCO METERING

Reliable Results. Every Meter. Every Time.



925 Canal Street, Bristol, PA 19007
• 215.228.0500
• tescometering.com

Field Testing
Catalog No.

P02-0802

Fiber Optic Coupled Ammeter

FUNCTIONALITY

A fiber optic cable connects the sensor to a receiver unit at ground potential, which contains the digital readout and an analog output. The instrument has no moving parts and does not require clamping onto the wire. The molded urethane housings are water resistant and will withstand high physical impact.

The analog output is the unique feature of this instrument. It is a reproduction of the high voltage current waveform, accurate to approximately the 50th harmonic, but available as a 0-2 volt AC signal at ground. This allows the use of many sophisticated low voltage instruments, such as scopes, waveform acquisition recorders, analyzers, and other analysis instruments which would previously not be usable at high voltage.

Designed to be used with your existing hot sticks.

SPECIFICATIONS

Range of Operation

- Current: 1-2000 True RMS Amps
- Voltage Environment up to 150 kV
- Accuracy: $\pm 0.75 \pm 1mV$ (1-2000A)
 - Phase: ± 1 Degree (1-2000A)

ABOUT TESCO

Since 1904, TESCO has been the trusted partner of electric utilities worldwide, delivering durable, precise, and innovative metering solutions designed for the real-world demands of the field and the laboratory. Our products are engineered and manufactured in the USA and backed by world-class technical expertise and support.

Reliable Results. Every Meter. Every Time.

Amp Sensor Opening

- Wide Sensor Opening Width: 3.86 in, 9.84 cm

Resolution: ± 0.1 mV

- 20 Ampere Measurement
Range: 1-19.99 A, 100 mV RMS per amp
- 200 Ampere Measurement
Range: 20-199.9 A, 10 mV RMS per amp
- 2,000 Ampere Measurement
Range: 200- 2,000 A, 1 mV RMS per amp

Output Impedance

- 50 ohms, minimum

Frequency Response

- 3000 Hz or to the 50th Harmonic

Fiber Optic Cable

- Length 40', 12.19 m
- Isolation 100 kV per foot, 500 kV max

Mechanical

- Wide Sensor Weight: 6.0 lbs, 2.73 kg
- Housing: Shock & water resistant molded urethane
- Hot stick Mounting: Universal chuck adapter (hot stick not included)
- Battery: Two each 9V alkaline or lithium; one per unit
- Battery Life: Minimum 4 hours of continuous use
- Operating temperature: -22° to $+140^{\circ}$ F, -30° to $+60^{\circ}$ C
- Lithium battery required for use below -4° F, -20° C

Contact TESCO Sales for configuration options and quotes.



Hook Accessory 600-0024
(purchased separately)