



THE EASTERN SPECIALTY COMPANY

# PURE SINE WAVE INVERTER

CAT. 1210

## ABOUT

TESCO's Power Inverter converts 12V battery power into pure sine wave AC household power, allowing you to run loads up to 1000 watts. With its state of the art, easy to use design, the inverter will offer you reliable service for providing AC power and 5V USB power from your service truck or van.

The Power Inverter's pure sine wave output is ideal for operating TESCO's Desktop Meter Stations or Field Test Interface Kits. Electronic equipment and circuitry are designed to operate with a pure sine wave.

## FEATURES

- 1,000 watts continuous power output
- 2,000 watts surge (peak power)
- Pure sine wave output
- Digital display for DC input voltage and AC output power
- LED power indicator
- Remote switch capable
- Dual GFCI outlet
- Built-in USB port
- Heavy-duty stud connectors

## SPECIFICATIONS

- Input: 12 VDC
- Output Voltage: 120 VAC, 60Hz
- Continuous Power: 1,000 W (8.3A)
- Surge Power: 2,000 W (16.6A)
- Output Waveform: Pure Sine Wave
- Dimensions: 7.3" x 12.2" x 3.5" (185 x 319 x 90 mm)
- Weight: 6.0 lbs.

